

Description

- New anti-vibration units, streamlined design, comfortable & big screen fluorescent display, legible
- Metal shield plate, magnetic, anti-jamming
- Change the traditional automatic power-off, the normal operation of uninterrupted power
- Full protection functions , anti-high voltage circuit design



Specifications

Brand :	LODESTAR
Model :	LD9801A
Quantity :	1
Color :	Yellow + black
Material :	Plastic housing
LCD Display :	60 x 28mm
Features :	Stable, precise, with capacity measurement and buzzer
Application :	Circuit test
Max. Display :	1999
DC Voltage :	200mV +/- (0.5% + 3), 2V +/- (0.5% + 3), 20V +/- (0.5% + 3), 200V +/- (0.5% + 3), 1000V +/- (1.0% + 5)
AC Voltage :	2V +/- (0.8% + 5), 20V +/- (0.8% + 5), 200V +/- (0.8% + 5), 700 / 750V +/- (1.2% + 5)
DC Current :	200uA +/- (0.8% + 3), 2mA +/- (0.8% + 3), 20mA +/- (0.8% + 3), 200mA +/- (1.2% + 4), 20A +/- (2.0% + 5)
AC Current:	20mA +/- (1.0% + 5), 200mA +/- (2.0% + 5), 20A +/- (3.0% + 10)
Resistance :	200 +/- (0.8% + 5), 2,000 +/- (0.8% + 3), 20,000 +/- (0.8% + 3), 200,000 +/- (0.8% + 3), 2,000,000 +/- (0.8% + 3), 200,000 +/- [(0.5% - 10) + 20] ohm
Capacitance :	20nF +/- (2.5% + 20), 200nF +/- (2.5% + 20), 2uF +/- (2.5% + 20), 200uF +/- (2.5% + 20)
Power Supply :	1 x 9V battery (included)
Certification :	CE
Packing List :	1 x Digital multimeter 2 x Probes (80cm-cable) 1 x 9V battery 1 x Chinese user manual)